

## High-voltage Power Supply (BL-3000E)



Technical specifications	
Cat. No.	BL-3000E
Type of Output	Constant-Voltage, Current or Power
Increment	1V, 1mA, 1W
Output Range	20--3000V, 1--400mA, 1--400W.
Timer Range	1min~99hr, 59min
V-hr Range	1~99999V-hr/ Increment 1V-hr
Display	LCD display with backlight
Output jacks	Four sets of output jacks

### Characteristic features:

- Touch keys, dual core microprocessor intelligent control;
- 0-9 digital button, make the operation more simple and convenient;
- Indicate the preset value and the actual output value at the same time;
- It can store 100 electrophoresis methods;
- With automatic memory function;
- With step-by-step control function (editable 10 groups, each group of up to make 10 program automatic connection operation);
- With a pause control function (including real-time tuning)
- With standard, timing, V-hr, step-by-step operation function;
- With constant voltage, constant current, constant power, misoperation, fault intelligent prompt functions;
- Automatic detection of no-load, over-load, short circuit, rapid resistance change, ground leak and system overheating.